

## Philips Dial Lamp Data

Type Number	Voltage (Volts)	Current (Amps)	Base	Philips Code	Fig.
	1.5	0.15	E 10	4822 134 40001	B
8057D	2.0	0.09			
8017 D 00	2.0	0.21			
8017 / 07	2.0	0.21	BA 9 S		
8017D	2.0	0.21			
	2.5	0.10	E 10	4822 134 40123	B
7111D	2.5	0.10			
6887D	2.5	0.20			
6890D	2.5	0.20			
7135D	2.5	0.30			
8096D	2.5	0.50			
	3.5	0.20	E 10	4822 134 40056	B
6888D	3.5	0.20			
6891D	3.5	0.20			
7136D	3.5	0.30			
7138D	3.8	0.30			
8041 D	4.0	0.10	E 10		A
8058D	4.0	0.10			
8047	4.0	0.11			
8047N	4.0	0.11			
	4.0	0.20	BA 9 S	4822 134 40157	D
8056D	4.0	0.20			
7126D	4.0	0.30			
8042	4.0	0.50			
8042 D 07	4.0	0.50			
7139D	4.5	0.30			
8038D	5.0	0.20			
8033D	5.0	0.20			
8033 D 07	5.0	0.20			
8055D	5.0	0.25			
7199D	6.0	0.03			
7121D	6.0	0.05			
	6.0	0.05	E 10	4822 134 40003	B
8063	6.0	0.07			
8059D	6.0	0.10			
8048W	6.0	0.15			
	6.0	0.18	E 10	4822 134 40004	B
8023D	6.0	0.18			
8023 N? /99	6.0	0.18	BA 9 S		D
9000D	6.0	0.21			
8054N	6.0	0.23			
7133D	6.0	0.25			
8079	6.0	0.30			
7140C	6.0	0.30			
7140D	6.0	0.30			

7141D	6.0	0.35			
7141C	6.0	0.35			
7148D	6.0	0.38			
8053	6.0	0.40			
8053D	6.0	0.40			
8001	6.0	0.40			
7142D	6.0	0.45			
4108	6.0	0.50			
8040	6.0	0.50			
8040W	6.0	0.50			
8046	6.0	0.50			
8046N	6.0	0.50			
8002D	6.0	0.50			
7143C	6.0	0.50			
7143D	6.0	0.50			
7198D	6.0	0.50			
8049N	6.0	0.57			
8049	6.0	0.60			
7145D	6.2	0.30			
7999 D 00	6.3	0.09			
8043	6.3	0.09			
8043D	6.3	0.09			
	6.3	0.10	E 10	4822 134 40005	B
8073D	6.3	0.10			
8073 D 00	6.3	0.10			
8073 D 07	6.3	0.10			
8006D	6.3	0.10			
8077D/98	6.3	0.10			
8078D/98	6.3	0.10			
	6.3	0.15	E 10	4822 134 40006	A
8008 N	6.3	0.15	BA 9 S		C
8009 D	6.3	0.25	E 10		A
8009 N	6.3	0.25	BA 9 S		C
8024 D	6.3	0.30	E 10		A
8024 N	6.3	0.30	BA 9 S		C
8045	6.3	0.32			
8045 D(00)	6.3	0.32	E 10		A
8045 D 07	6.3	0.32			
8045 / 37	6.3	0.32			
8091 D (00)	6.3	0.64	E 10		A
8025D	6.5	0.45			
7994 N (00)	7.2	0.10	BA 9 S		C
7181D	8.0	0.05			
7185D	8.0	0.45			
7186D	8.0	0.50			
8066N	9.0	0.20			
8066	9.0	0.24			

8034 D(00)	10.0	0.20	E 10		A
8080	10.0	0.20			
8080D	10.0	0.20			
8092D	10.0	0.20			
8092 D 00	10.0	0.20			
8092 D 07	10.0	0.20			
8007D	10.0	0.20			
8010T	10.0	0.20			
8070N	10.0	0.20			
7193D	10.0	0.45			
210	12.0	0.06			
8089 D(00)	12.0	0.10	E 10		B
8089 N(00)	12.0	0.10	BA 9 S		D
8003D	12.0	0.10			
8072D	12.0	0.10			
8075D/98	12.0	0.10			
8076D/98	12.0	0.10			
8060D	14.0	0.15			
	15.0	0.20	E 10	4822 134 40013	A
8004D	15.0	0.20			
8011T	15.0	0.20			
8005D	18.0	0.10			
8064	18.0	0.20			
8064N	18.0	0.20			
8012T	18.0	0.20			
8095D	19.0	0.09			
8097 D	19.0	0.097	E 10		A
	24.0	0.05	E 10	4822 134 40065	A




Fig A.



Fig B.




Fig C.




Fig D.

This information is based on data from "Mario's Place" website at <http://www.datastress.com/~mario/radio/radio.shtml>